

ECMA/TC38-TG3/2015/026 (Rev. 1 – 15 April 2017)

Annex B2 - Product environmental attributes Desktop/All-in-One Computers

The declaration may be published only when all rows and/or fields marked with * are filled-in (n.a. for not applicable). Additional information regarding each item may be found under P15.

Brand *	Lenovo	Logo
Company name *	Lenovo	and the second second second second
Contact information *	Lenovo Global Environmental Affairs	Lenovo
e-mail address	Alvin L Carter	LEI IOVO.
	alcarter@lenovo.com	and the second se
Internet site *	http://www.lenovo.com/social_responsibility/us/en/environment	.html
Additional information	The latest version of this document can be found at:	
	http://www.lenovo.com/ecodeclaration	

The company declares (based on product specification or test results based obtained from sample testing), that the product						
conforms to the statement	conforms to the statements given in this declaration.					
Type of product *	All in one computer					
Commercial name *	IdeaCentre AIO 3 27ALC6					
Model number *	F0FY					
Issue date *	2021/4/23					
Intended market *	🛛 Global 🔲 🗖 Europe 📄 Asia, Pacific & Japan 📄 Americas 📄 Other					
Additional information						

This is an uncontrolled copy when in printed form. Please refer to the contact information for the latest version.

About Annex B2

Annex B2 reflects Product environmental attributes relevant for Computers and Computer Monitors. The following items from the ECMA-370 Main body are not shown in the template:

P4.1 – P4.3 Consumable materials

P9.1 TEC and Print speed

P10.2 - P10.3 Chemical emissions from printing products

P11.1 - P11.3 Consumable materials for printing products.

Model n	umber *	F0FY Logo	Long		
Issue date *		2021/4/23	Lend	JVC)
Produc	t environ	mental attributes - Legal requirements	Require	ment	met
Item			Yes	No	n.a.
P1		bus substances and preparations			
P1.1*		s do comply with current European RoHS Directive. (See legal reference and NOTE B1)	\square		
P1.2*	Comme	s do not contain Asbestos (see legal reference). nt: Legal reference has no maximum concentration value.	\square		
P1.3*	hydrobro trichloro	s do not contain Ozone Depleting Substances: Chlorofluorocarbons (CFC), pmofluorocarbons (HBFC), hydrochlorofluorcarbons (HCFC), Halons, carbontetrachloride, 1,1,1- ethane, methyl bromide (see legal reference). Comment: Legal reference has no maximum ration values.			
P1.4*	terpheny	s do not contain more than; 0,005% polychlorinated biphenyl (PCB), 0,005% polychlorinated /l (PCT) in preparations (see legal reference).	\boxtimes		
P1.5*	chain co	s do not contain more than 0,1% short chain chloroparaffins (SCCP) with 10-13 carbon atoms in th ntaining at least 48% per mass of chlorine in the SCCP (see legal reference).			
P1.6*	(see leg	th direct and prolonged skin contact do not release nickel in concentrations above 0,5 μg/cm²/weel al reference). nt: Max limit in legal reference when tested according to EN1811:2011-5.	< 🔀		
P1.7*	REACH	Article 33 information about substances in articles is available at (add URL or mail contact): www.lenovo.com/us/en/Lenovo-REACH-SVHC-Disclosure	\square		
P2	Batterie				
P2.1*	If the pro symbol.	oduct contains a battery or an accumulator, the battery/accumulator is labeled with the disposal Information on proper disposal is provided in user manual. (See legal reference)	\square		
P2.2*	Batteries referenc	s or accumulators do not contain more than 0,0005% of mercury or 0,002% of cadmium. (See lega e)	I 🛛		
P2.3*	Batteries	s and accumulators are readily removable. (See legal reference)	\boxtimes		
P3	Confor	nity verification & Eco design (ErP)			
P3.1*	The Dec	duct is CE-marked to show conformance with applicable legal requirements (see legal reference). Itaration of Conformity can be requested at (add link or e-mail address): www.lenovo.com/us/en/compliance/eu-doc			
P3.2*	The pro	duct complies with the Eco design requirements for energy-related products, al reference).	\boxtimes		
		d information is; available at (add URL): www.lenovo.com/us/en/compliance/eco-declaration			
P5		packaging			
P5.1*	Packagi	ng and packaging components do not contain more than 0,01% lead, mercury, cadmium ar ent chromium by weight of these together.	d 🔀		
P5.2*	The pac	kaging materials are marked with abbreviations and numbers indicating the nature of the material(e legal reference).	s) 🔀		
P5.3*	The prod (see leg	Juct packaging material is free from ozone depleting substances as specified in the Montreal Protoc al reference). nt: Legal reference has no maximum concentration values.	ol 🔀		
P6		nt information			
					_

NOTE B1 Restriction applies to the homogeneous material, unless other specified and expressed in weight %. Stating "Yes" means that the product is compliant with the mandatory requirements.

Model nu	umber *	F0FY	Logo	Lon	-	
Issue da	te *	2021/4/23		Len	ove	2
Product		mental attributes - Market requirements (See General NOTE GN	l below)	_		
l tra una		onmental conscious design		Require		
Item P7		tory to fill in. Additional information regarding each item may be found under P14. Disassembly, recycling		Yes	No	n.a.
P7.1*		at have to be treated separately are easily separable				
P7.2*		naterials in covers/housing have no surface coating.			Ħ	
P7.3*		arts > 100 g consist of one material or of easily separable materials.			Ħ	
P7.4*	-	arts > 25 g have material codes according to ISO 11469 referring ISO 1043-4.			Ħ	Ē
P7.5	Plastic p	arts are free from metal inlays or have inlays that can be removed with commonly	available tools.		Ē	
P7.6*	Labels a	re easily separable. (This requirement does not apply to safety/regulatory labels).			Ē	
	Product	lifetime				
P7.7*	Upgradir	ng can be done e.g. with processor, memory, cards or drives		\boxtimes		
P7.8*	Upgradir	ng can be done using commonly available tools		\boxtimes		
P7.9	Spare pa	arts are available after end of production for: 5 years				
P7.10	Service i	is available after end of production for: 5 years				
		and substance requirements				
P7.11*	Material		rial type: PC			
P7.12	Insulatio	n materials of external electrical cables are PVC free.			\boxtimes	
P7.13		n materials of internal electrical cables are PVC free.			\boxtimes	
P7.14	weight (polyviny	plastic casing/cover parts > 25 g contain no more than 0,1% weight (1000 ppm) 1000 ppm) chlorine attributable to brominated flame retardants, chlorinated flam I chloride or 0,3% weight (3000 ppm) bromine and 0,3% weight (3000 ppm) chlorine an 25% post-consumer recycled content.	ne retardants, a	and		
P7.15	Printed of as define	circuit boards, PCBs (without components) are low halogen: all ⊠ PCBs > 25 g [ed in IEC 61249-2-21. (See 1NOTE B2)	are low halog	jen 🗌	\square	
P7.16	Marking:			\boxtimes		
P7.17	TBBF	hemical specifications of flame retardants in printed circuit boards > 25 g (without PA (additive), ⊠TBBPA (reactive) (See NOTE B3),⊠Other: <i>aromatic brominat</i> 9003-35-4		s, 🛛		
		hemical specifications of flame retardants in printed circuit boards (without compo ig ISO 1043-4:	nents) > 25 g			
P7.18	concentr 1. Chem	lame retarded plastic parts > 25 g contain the following flame retardant substanc rations above 0,1%: iical name: confidential , CAS #: confidential (See NOTE B4) iical name: , CAS #: "	ces/preparations	in 🔀		
	3. Chem	<pre>iical name: , CAS #: " hemical specifications of flame retardants in plastic parts > 25 g according ISO 10</pre>	43-4: >ABS+PC	- 🖂		
P7.19	In plastic	c parts > 25 g, flame retardant substances/preparations above 0,1% are used which d the following Risk phrases; and Hazard statements:	ch have been			
			(See note B5)			
P7.20*	Postcon	sumer recycled plastic material content is used in the product (See Note B6):		\boxtimes		
	a) Of t a p or	at least one of the two alternatives below shall be answered; total plastic parts' weight > 25 g, the postconsumer recycled plastic material conte ercentage of total plastic by weight) is 11.76% . (black) 11.32% . (White) e weight of recycled material is 178.7 g. (black) 178.7 g. (White)	ent (calculated a	S		

GENERAL NOTE Standard references should direct to the latest version of a standard. If an older version of a standard is used, section P15 shall be used for explanation.

NOTE B2 IEC 61249-2-21 defines maximum limits of 900 ppm for each of the substances chlorine and bromine and a maximum limit of 1500ppm of these substances combined. The standard does not address fluorine, iodine and astatine which are included in the group of halogens.

NOTE B3 and B4 A Guidance document on Chemical substances is available; see http://www.ecma-international.org/publications/standards/Ecma-370.htm

NOTE B5 If a certain substance has been assigned a certain risk phrases / hazard statement in the referenced source, this does not necessarily mean the substance has been tested for all of the hazards referred to by a certain customer.

NOTE B6 Applies to a product containing plastic parts whose combined weight exceeds 100 g with the exception of printed circuit boards, cables, connectors and electronic components and bio-based plastic material.

Model number * Issue date *	F0FY 2021/4/23	Logo	Lenovo
Product environm	nental attributes - Market requirements (continued)	+	Requirement met

Item

Requirement met Yes No n.a.

	Material and su	ibstance requirements	(continued)			
P7.21*		c material content is use		NOTE B7):		
	If YES at least	one of the two alternative	es below shall be ans	wered.		_
	a) Of total pla	stic parts' weight > 25 g			lated as a percentage of	
		by weight) is %.				
	or b) The weight	of the biobased plastic	material is a			
P7.22*		re free from mercury, i.e.		D.		
==		ed specify: Number of la		mum mercury content p		
P8	Batteries					
P8.1*	,	I composition: Mangane	ese dioxide			
P9		nption (See NOTE B8)				
P9.1		the following power leve Power level at	els or energy consump Power level at	tions are reported: Power level at	Deference/Standard for anormy	
Energy mo	bde	100 V AC	115 V AC	230 V AC	Reference/Standard for energy modes and test method *	
Peak (On-	·max)	90 W	90 W	90 W	Full load	
Categor	·v2					
Short Idle Enabled	State - WOL	20.80 W	20.14 W	20.75 W	Use for ENERGY STAR V8 registration (P _{idle})	
	State - WOL	6.03 W	6.26 W	6.44 W	Use for ENERGY STAR V8	
Enabled					registration (P _{idle})	
Sloop (S2) - WOL Enabled	0.62 W	0.65 W	0.71 W	Use for ENERGY STAR V8	
Sieep (33)		0.02 VV	0.05 W	0.77 00	registration(P _{sleep})	
Off (S5) -	WOL Enabled	0.23 W	0.25 W	0.32 W	Use for ENERGY STAR V8 registration(P _{off})	
EPS No-lo		W	W	W		
(External power wall outlet but dis	supply / charger plugged in t sconnected from the product	he .)				
PTEC *		W	W	W		\boxtimes
	ergy Consumption				E (0700(1000) (D 0 15	
ETEC * Annual En	ergy Consumptior		61.30 kWh/year	63.39 kWh/year	$E_{TEC} = (8760/1000) \times (P_{off} \times 0.45) + P_{sleep} \times 0.05 + P_{long_{ldle}} \times 0.15 + P_{short_{ldle}} \times 0.35)$	
Estern al D					DL Enabled; P _{idle} : Idle State - WOL Enabled	<u> </u>
	,	ency Level (Internationa	ai Efficiency Marking P			<u> </u>
	solution * : 2.07 m					<u>Ц</u>
	0,	save mode: 25 minutes				<u> </u>
P9.2*		ut the energy save funct	•	e product.		<u> </u>
P9.3		y class (monitors only):	N/A			\square
P10	Emissions	Declared	- ISO 0200 (0 NOT			
P10.1	Noise emission Mode	Declared according t Mode description	0 150 9296 (See NOT		nit A-weighted sound power level, L _{WA c}	(B)
1 10.1	Idle	* HDD idle		* 2.8	The A-weighted Sound power level, L _{WA,c}	
	Operation	* HDD Operating		* 2.9		⊢⊢
	Other mode	Declared A-weighted sour	nd pressure level (dB) 1		ion desktop – idle)	
	Other mode	Declared A-weighted sour			ion desktop – operating)	
	-				ion desktop – operating/	
	Measured accor	rding to: 🔀 ISO 7779 L Other	_ ECMA-74 (only if not covered b	$P_{\rm MA-74}$		
	I					

NOTE B7 The following is to be excluded from the calculation of percentage: printed circuit boards, labels, cables, connectors and electronic components and postconsumer recycled plastic

NOTE B8 A Guidance document on Energy Efficiency is available; see <u>http://www.ecma-international.org/publications/standards/Ecma-370.htm</u>

NOTE B9 A Guidance document on Acoustic Noise is available; see http://www.ecma-international.org/publications/standards/Ecma-370.htm

Model nu	umber *	F0FY		Logo	Long		
lssue da	te *	2021/4/23			Leno	vo	
Product	environ	nental attributes - Market requirements (continue	ed)	•	Require	ment	me
Item					Yes	No	n.a
	Electro	nagnetic emissions					
P10.4	program	er display meets the requirement for low frequency electror (s): CE,FCC,VCCI,C-Tick	nagnetic fields of the fol	lowing volunta	ry 🔀		
P12		nics for computing products					
P12.1*		lay meets the ergonomic requirements of ISO 9241-307 fo		ogies.		\boxtimes	
P12.2*	The phy	sical input device meets the requirements of ISO 9995 and	ISO 9241-410.			X	
P13	Packag	ng and documentation					
P13.1*	Product Product Product	packaging material type(s): <i>Plastic-Solid EPE</i> weigh	nt (kg): 0.4322 nt (kg): 0.4128 nt (kg): 0.0405				
P13.2*	Product	plastic primary packaging is free from PVC.			\boxtimes		
P13.3*		uct primary corrugated fiberboard packaging, specify the recovered fiber content: 80 %	e contained percentage	e of minimum			
P13.4*		nedia for user and product documentation (tick box): ronic, XPaper, Other					
P13.5	Ùser an	only complete this item if paper documentation used) I product documentation on paper media is chlorine-free: ease specify:					
	Totally of	hlorine-free			\boxtimes		
		al chlorine-free			E E		
	Process	ed chlorine-free			H		
P14	Volunta	ry programs					
P14.1		luct meets the requirements of the following voluntary prog	ıram(s):				
	Eco-lab Eco-lab Eco-lab	I: Criteria version: Date	Product	category: category: category:			
P15		nal information (See NOTE B10)					
P9		consumption of specific configuration may vary; desci 5300U, Ryzen 5 5500U, Ryzen 7 5700U ; GPU : NA ; RA)
	informat knowled	Supplier makes no representations, guarantees, assurance on contained in this document. All information provided by ge available at the time of completion, and supplier shall ha here is approximate and provided for informational purpos on.	supplier in this docume ave no obligation to upd	nt is provided l ate such inforn	based on supp nation. The inf	olier's format	ion
P9	See Ene	rgy Star Qualified Notebooks & Tablet Computers for the li w.energystar.gov/index.cfm?fuseaction=find_a_product.sh		_code=CO			

NOTE B10 Additional lines may be inserted to declare further items, by positioning the cursor at the far right of the row and hitting the <Enter> key.

Legal references Europe Annex B2

Reference	Declaration item
Directive 2011/65/EU (RoHS Directive) * * Specific exemptions apply for certain products and applications.	P1.1
Regulation (EC) 1907/2006(REACH, Annex XVII	P1.2, P1.4, P1.6, P1.7
Regulation (EC) 2037/2000, 2038/2000, 2039/2000 (Marketing and use of Ozone layer depleting substances)	P1.3, P5.3
Norwegian regulation relating to restrictions on the use of certain dangerous chemicals 20.12.2002	P1.5
Directive 2013/56/EC (Battery and accumulators Directive) * * These provisions shall not apply where, for safety, performance, medical or data integrity reasons, continuity of power supply is necessary and requires a permanent connection between the appliance and the battery or accumulator.	P2.1, P2.2, P2,3, P8.1
Directive 2006/95/EC (Low Voltage Directive)	P3.1
Directive 2004/108/EC (EMC Directive)	P3.1
Directive 1999/5/EC (R&TTE Directive)	P3.1
Regulation (EC) 801/2013 amending Regulation (EC) No 1275/2008 with regard to ecodesign requirements for standby, off mode electric power consumption of electrical and electronic household and office equipment, and amending Regulation (EC) No 642/2009 with regard to ecodesign requirements for televisions	P3.1, P3.2
Regulation (EC) No 1272/2008 (CLP Regulation)	P7.19
Directive 2004/12/EC (Packaging Directive)	P5.1
Decision 97/129/EC (Secondary packaging legislation)	P5.2
Directive 2012/19/EU (WEEE directive)	P6.1

Lenovo ErP Lot3 Information Sheet - PC / Notebook -

As required by COMMISSION REGULATION (EU) No 617/2013 of 26 June 2013 implementing Directive 2009/125/EC of the European Parliament and of the Council with regard to ecodesign requirements for computers and computer servers (ErP Lot3).

Products scope of this sheet:

Desktop computer, integrated desktop computer, and notebook computer

This document is only valid in connection with the IT Eco Declaration of the specific Product.

Commercial name	IdeaCentre AIO 3 27ALC6	Logo
Model Number	FOFY	Longua
Issue Date	2021/4/23	Lenovo.
Additional information		

(d)	year of manufacture:				2021
(e)	Etec value (kWh) per ErP Lot 3 Categor disabled and if the system is tested with				cards (dGfx) are
f)	Etec value (kWh) per ErP Lot 3 Categor enable	ry and capability adjust	ments applied when a	II discrete graphics o	cards (dGfx) are
		Category A (according to ErP Lot 3)	Category B (according to ErP Lot 3)	Category C (according to ErP Lot 3)	Category D (according to ErP Lot 3)
	Memory over base [GB]				16
ents ting	Additional internal storage	(Yes / No)	(Yes / No)	(Yes / No)	Yes (Yes / No)
idjustme ring tes	Discrete television tuner	(Yes / No)	(Yes / No)	(Yes / No)	No (Yes / No)
capability adjustments applied during testing	Discrete Audio Card	(Yes / No)	(Yes / No)	(Yes / No)	No (Yes / No)
cap; app	Discrete graphics Card(s) [number / #]	#: (Yes / No)	# <u>:</u> (Yes / No)	# <u>:</u> (Yes / No)	No #: (Yes / No)
	Category of discrete graphics Card(s)				NA
sults	Etec Value (kWh) - dGfx disabled all discrete graphics cards (dGfx) are disabled/ UMA is active for switchable graphics/ product has no graphics cards (dGfx)				23.09
Test results	Etec Value (kWh) - dGfx enabled all discrete graphics cards (dGfx) are enabled				NA
(g)	Idle state power demand (Watts);				6.02
h)	Sleep mode power demand (Watts);				0.738
i)	Sleep mode with WOL enabled power de	emand (Watts) (where	enabled);		0.769
j)	Off mode power demand (Watts);				0.342
k)	Off mode with WOL enabled power dem	and (Watts) (where en	abled);		0.344
[])	Internal power supply efficiency at 10 %	, 20 %, 50 % and 100 °	% of rated output pow	er (if applicable):	
	10% 20% 50%	100% Avera	ige		
m)	External power supply efficiency (if appli	cable)*:			
	Average active efficiency: 90W Level V	l (88.5%);			
	*internal note: show values for all available external p				
0)	Minimum number of loading cycles that	the batteries can withs	tand (applies only to n	otebook computers):	N/A
p-1)	Measurement methodology used to dete	ermine information mer	itioned in points (I) – ii	nternal PSU efficiency:	:
(p-2)	Measurement methodology used to dete	ermine information mer	tioned in points (m) – nd a.ca.c. power su		cy:

(p-3)	Measurement methodology	used to determine information men	ioned in points (o) – loading cycles batteries:	
(p-4)			ioned in maximum, idle, sleep, off mode n:	
			rs-Measurement of energy consumption	
(q)		eving a stable condition with respect		
(r)		on user manual/Power on->Wait 5 nd/or off mode was selected or progr		
		Based on user manual-Set power	button behaviors	
	Set power butto	n behaviors		
		power button does according to yo urn off the computer or put the com	ur preference. For example, by pressing the puter to sleep or hibernation mode.	
	To change what the pow	ver button does:		
	1. Go to Control Pane	and view by large icons or small ic	ons.	
	2. Click Power Option	ns \rightarrow Choose what the power butt	ons do.	
	3. Change the settings	as you prefer.		
(s)	Sequence of events require off mode:	ed to reach the mode where the equi	pment automatically changes to sleep and/or	
	Based on user manual/	Control Panel->Power Options-> 0 for this plan	hange Settings-> Restore default settings	
(t)		dition before the computer autom	atically reaches sleep mode, or another	25 minutes
(u)	Length of time after a per	iod of user inactivity in which the	requirements for sleep mode (in minutes): computer automatically reaches a power	
(v)		wer demand requirement than sleep display sleep mode is set to active	ate after user inactivity (in minutes):	10 minutes
		saving potential of power manageme		
(w)	Information on the energy-		nt functionality:	
(w)	Information on the energy- User information on how to Set the power pla For ENERGY STAR® com been idle for a specified o	saving potential of power management N/A enable the power management funct Based on user manual-Set the pliant computers, the following power	nt functionality:	
(w)	Information on the energy- User information on how to Set the power pla For ENERGY STAR® com been idle for a specified o	saving potential of power manageme N/A enable the power management func Based on user manual-Set the In pliant computers, the following power uration: (when plugged into ac power) r 10 minutes	nt functionality: tionality: ne power plan	
(w)	Information on the energy- User information on how to Set the power pla For ENERGY STAR® com been idle for a specified of Table 1. Default power plan • Turn off the display: Afte • Put the computer to slee	saving potential of power manageme N/A enable the power management func Based on user manual-Set the In pliant computers, the following power uration: (when plugged into ac power) r 10 minutes	nt functionality: stionality: ne power plan plan takes effect when your computers have	
(w)	Information on the energy- User information on how to Set the power plat For ENERGY STAR® com been idle for a specified of <i>Table 1. Default power plan</i> • Turn off the display: Afte • Put the computer to slee To awaken the computer To reset the power plan to 1. Go to Control Panel	saving potential of power management N/A enable the power management funct Based on user manual-Set the m pliant computers, the following power uration: (when plugged into ac power) r 10 minutes p: After 25 minutes	nt functionality: stionality: plan takes effect when your computers have ur keyboard.	
(w) (x)	Information on the energy- User information on how to Set the power plat For ENERGY STAR® com been idle for a specified of <i>Table 1. Default power plan</i> • Turn off the display: Afte • Put the computer to slee To awaken the computer To reset the power plan to 1. Go to Control Panel 2. Click Power Options	N/A N	nt functionality: stionality: plan takes effect when your computers have ur keyboard.	
(w) (x)	Information on the energy- User information on how to Set the power pla For ENERGY STAR® com been idle for a specified of <i>Table 1. Default power plan</i> • Turn off the display: Afte • Put the computer to slee To awaken the computer To reset the power plan to 1. Go to Control Panel 2. Click Power Options Test parameters for measu the electricity supply system used for electrical testing:	N/A N/A In a second seco	nt functionality: tionality: te power plan plan takes effect when your computers have ur keyboard. ur keyboard. ter plan of your preference. quency in Hz, — total harmonic distortion of on the instrumentation, set-up and circuits in Hz: 230V/50Hz	
(w) (x)	Information on the energy- User information on how to Set the power pla For ENERGY STAR® com been idle for a specified of <i>Table 1. Default power plan</i> • Turn off the display: Afte • Put the computer to slee To awaken the computer To reset the power plan to 1. Go to Control Panel 2. Click Power Options Test parameters for measu the electricity supply system used for electrical testing:	N/A In the power management function Based on user manual-Set tf Based on user manual-Set tf Definition Definit Definition Definition Definition Definition	nt functionality: tionality: te power plan plan takes effect when your computers have ur keyboard. ur keyboard. ter plan of your preference. quency in Hz, — total harmonic distortion of on the instrumentation, set-up and circuits in Hz: 230V/50Hz ify supply system: ≤2%	
w) (x)	Information on the energy- User information on how to Set the power pla For ENERGY STAR® com been idle for a specified of <i>Table 1. Default power plan</i> • Turn off the display: Afte • Put the computer to slee To awaken the computer To reset the power plan to 1. Go to Control Panel 2. Click Power Options Test parameters for measu the electricity supply system used for electrical testing:	N/A enable the power management funce Based on user manual-Set tf Based on user manual-Set tf In pliant computers, the following power uration: (when plugged into ac power) r 10 minutes p: After 25 minutes from Sleep mode, press any key on yo c achieve the best balance between pe and view by large icons or small icons a, and then choose or customize a power mements: — test voltage in V and free m, — information and documentation Test voltage in V and frequency harmonic distortion of the electric	nt functionality: tionality: te power plan plan takes effect when your computers have ur keyboard. ur keyboard. ter plan of your preference. quency in Hz, — total harmonic distortion of on the instrumentation, set-up and circuits in Hz: 230V/50Hz	
w) x)	Information on the energy- User information on how to Set the power plat For ENERGY STAR® com- been idle for a specified of <i>Table 1. Default power plan</i> • Turn off the display: Afte • Put the computer to slee To awaken the computer To reset the power plan to 1. Go to Control Panel 2. Click Power Options Test parameters for measu the electricity supply system used for electrical testing: <i>Total</i> Instrument	Saving potential of power management N/A Penable the power management funce Based on user manual-Set tf Deliant computers, the following power Uration: (when plugged into ac power) r 10 minutes p: After 25 minutes from Sleep mode, press any key on you b achieve the best balance between per and view by large icons or small icons b, and then choose or customize a power rements: — test voltage in V and free m, — information and documentation Test voltage in V and frequency harmonic distortion of the electrice Range Used	nt functionality: tionality: te power plan plan takes effect when your computers have ur keyboard. ur keyboard. ter plan of your preference. quency in Hz, — total harmonic distortion of on the instrumentation, set-up and circuits in Hz: 230V/50Hz ify supply system: ≤2%	
w) (x)	Information on the energy- User information on how to Set the power plat For ENERGY STAR® com- been idle for a specified of <i>Table 1. Default power plan</i> • Turn off the display: Afte • Put the computer to slee To awaken the computer To reset the power plan to 1. Go to Control Panel 2. Click Power Options Test parameters for measu the electricity supply system used for electrical testing: Total Instrument Type	N/A enable the power management funct Based on user manual-Set tf m pliant computers, the following power uration: (when plugged into ac power) r 10 minutes p: After 25 minutes from Sleep mode, press any key on you achieve the best balance between pe and view by large icons or small icons a, and then choose or customize a pow rements: — test voltage in V and frequency harmonic distortion of the electrice Range Used Or ***	nt functionality: ttionality: te power plan plan takes effect when your computers have ur keyboard. ur keyboard. ter plan of your preference. quency in Hz, — total harmonic distortion of on the instrumentation, set-up and circuits in Hz: 230V/50Hz ity supply system: ≤2% Make and Model **	
(x) (x) (z)	Information on the energy- User information on how to Set the power plat For ENERGY STAR® com been idle for a specified of <i>Table 1. Default power plan</i> • Turn off the display: Afte • Put the computer to slee To awaken the computer To reset the power plan to 1. Go to Control Panel 2. Click Power Options Test parameters for measu the electricity supply system used for electrical testing: Total Instrument Type AC Power Source	Saving potential of power management N/A enable the power management funct Based on user manual-Set the In pliant computers, the following power uration: (when plugged into ac power) r 10 minutes p: After 25 minutes from Sleep mode, press any key on yoo achieve the best balance between per and view by large icons or small icons and then choose or customize a power irrements: — test voltage in V and free m, — information and documentation Test voltage in V and frequency harmonic distortion of the electrice Range Used Or *** 230V;50Hz 0~200V;0~20A	nt functionality: tionality: te power plan plan takes effect when your computers have ur keyboard. rformance and power saving: ter plan of your preference. quency in Hz, — total harmonic distortion of on the instrumentation, set-up and circuits in Hz: 230V/50Hz ity supply system: ≤2% Make and Model ** EXTECH;6810;SN:1450172 YOKOGAWA;WT210;SN:91H427511	
(w) (x)	Information on the energy- User information on how to Set the power plat For ENERGY STAR® com- been idle for a specified of <i>Table 1. Default power plan</i> • Turn off the display: Afte • Put the computer to slee To awaken the computer To reset the power plan to 1. Go to Control Panel 2. Click Power Options Test parameters for measu the electricity supply system used for electrical testing: <i>Total</i> Instrument Type AC Power Source Power Meter	Saving potential of power management N/A enable the power management funct Based on user manual-Set the In pliant computers, the following power uration: (when plugged into ac power) r 10 minutes p: After 25 minutes from Sleep mode, press any key on yoo achieve the best balance between per and view by large icons or small icons and then choose or customize a power irrements: — test voltage in V and free manonic distortion of the electrico Range Used Or *** 230V;50Hz	nt functionality: tionality: te power plan plan takes effect when your computers have ur keyboard. rformance and power saving: ter plan of your preference. quency in Hz, — total harmonic distortion of on the instrumentation, set-up and circuits in Hz: 230V/50Hz ity supply system: ≤2% Make and Model ** EXTECH;6810;SN:1450172	

	Battery[ies] not user replaceable	Battery[ies] user replaceable	n/a
	The battery[ies] in this product cannot be easily replaced by users themselves. ¹⁾		
Internal/built-in Battery			\boxtimes
External/detachable Battery			
Bios Backup Battery	\boxtimes		
Other:			
Additional information			

1) The battery[ies] in this product cannot be easily replaced by users themselves.

Акумулаторната[ите] батерия[и] в този продукт не може да се замени[ят] лесно от самите потребители.

Las baterías de este producto no pueden ser sustituidas fácilmente por los propios usuarios. Výměnu baterie/baterií v tomto výrobku by neměli provádět sami uživatelé. Brugeren kan ikke uden videre udskifte batteriet/batterierne i dette produkt.

Der Akku/die Akkus dieses Produkts kann/können nicht ohne weiteres vom Benutzer selbst ausgetauscht werden. Kasutajad ei saa selle toote akut/akusid ise hõlpsasti asendada.

Η μπαταρία[-ες] στο προϊόν αυτό δεν μπορούν να αντικατασταθούν εύκολα από τους ίδιους τους χρήστες

La/les batterie(s présente(s) dans ce produit ne peuvent être facilement remplacée(s) par les utilisateurs eux-mêmes. Korisnik ne može lako zamijeniti Bateriju sam u ovom proizvodu.

La batteria/le batterie in questo prodotto non può/possono essere facilmente sostituita/e dall'utente. Lietotăji paši nevar nomainît šă ražojuma akumulatoru(-us). Šio gaminio baterijos [bateriju] pats vartotojas negali lengvai pakeisti. A termék akkumulátorát/akkumulátorait a felhasználó nem tudja egyedül egyszerűen kicserélni.

Il-batterija/batteriji f'dan il-prodott ma tistax/jistgħux tiġi/jiġu sostitiwita/i mill-utenti stess. Batteriet [ene] i dette produktet kan ikke lett erstattes av brukerne selv.

De batterij(en) in dit product is (zijn) door de gebruiker niet gemakkelijk vervangbaar.

Użytkownik nie może sam w łatwy sposób wymienić baterii w tym produkcie. A ou as baterias deste produto não podem ser facilmente substituídas pelos próprios utilizadores.

Bateria (bateriile) din acest produs nu poate (pot) fi ușor înlocuită (înlocuite) de utilizatorii înșiși.

Batériu(-ie) v tomto výrobku nemôže výmieňať používateľ. Baterij/baterije v tem izdelku uporabniki sami ne morejo zlahka zamenjati.

Tämän tuotteen akku [akut] ei[vät] ole helposti käyttäjän vaihdettavissa.

Det är inte enkelt för kunden att själv byta ut batteriet/batterierna. Bu üründeki batarya(lar) kullanıcılar tarafından kolaylıkla değiştirilemez.